

EP-booster

DISCRETE PRE-AMP

Congratulations on purchasing the Xotic EP-Booster!! The EP-Booster is a discrete FET preamp with low impedance output providing up to +20db of unadulterated boost that's multi-dimensional with shimmering highs and lows. The internal DIP switches let you choose the boost level and EQ setting. The EP-Booster can be powered by 9-volt up to 18-volts for desired headroom.



Specs:

Dimensions (W/D/H): 3.5" x 1.5" x 1.5"
(89mm X 38mm X 38mm)

Weight: 0.57 lbs. (260g)

True Bypass Switching

Power Consumption: 9VDC/5mA

Battery Type: 9VDC (006P) x 1


AC Adapter (Optional): 9VDC-18VDC

Negative Tips (Regulated only)

Input Impedance: 1M ohm

Output Impedance: 1K ohm (min.) / variable

DEFAULT SETTINGS




1 +3DB GAIN - ON
2 BRIGHT SWITCH - ON (FLAT EQ)

UNITY GAIN SETTINGS




1 +3DB GAIN - OFF
2 BRIGHT SWITCH - ON (FLAT EQ)

VINTAGE SETTINGS



1 +3DB GAIN - OFF
2 BRIGHT SWITCH - OFF



Inside view